

# **K256BB Transmission System**

## **Transmitter Power Output Calculations**

This exhibit has been included to explain the basis for the transmitter power output utilized to achieve the authorized effective radiated power of 0.024 kW.

The antenna system consists of a vertically polarized Scala FM-V antenna. The antenna has a power gain of 1.26 at 99.1 MHz. Therefore, an antenna input power of 19 watts is required to achieve 0.024 kW.

The transmission line used to get from the transmitter to the antenna input is Andrew LDF5-50 (7/8 inch) Low Density Foam heliax. With 13.7 meters of length, the transmission line attenuation is 0.19 dB yielding an efficiency of 95.62%. Therefore, a power of 20 watts is required at the input of the transmission line, which is also the transmitter output, to achieve the authorized effective radiated power.

### **Feed System Efficiency:**

In calculating the Feed System Efficiency, the following values were used based on the insertion loss data provided by each manufacturer.

Andrew LDF5-50 Heliax (13.7 meters)  
Insertion Loss = 0.19 dB (at 99.1 MHz)

### **Antenna Gain:**

In calculating the Antenna Gain, the following value was used based on data provided by the manufacturer:

Scala FM-V  
Power Gain: 1.26 dB

### **TPO Calculations:**

$$\begin{array}{rcl} \text{Effective Radiated Power} & & \\ \hline & = & \text{TPO} \\ (\text{Antenna Power Gain} * \text{Feed System Efficiency}) & & \\ \\ & & \\ 0.024 \text{ kW} & & \\ \hline & = & \underline{\underline{0.020 \text{ kW} = 0.02 \text{ kW TPO}}} \\ (1.26 * 95.62\%) & & \end{array}$$