IM Measurements Taken in

Product Frequency (MHz)	Transmitter Frequency (MHz)	Interfering Frequency (MHz)	Pad (dB)	Bandpass Filter Loss (dB)	Total Loss	Full Scale Range (dBµ)	Scale Reading (dBµ)	Adjusted Level (dBµ)	Carrier Reference Level (dBµ)	Level Referenced to Carrier (dB)	Notes*
Transmitter Mixes											
	97.7	**Ref.**	**6**		**6**	**120**			**126**		Not Operational from this Site
	101.9	**Ref.**	**6**		**6**	**120**	**5.7**		**120.3**		
	102.7	**Ref.**	**6**		**6**	**120**	**6.4**		**119.6**		
	104.5	**Ref.**	**6**		**6**	**120**	**5.5**		**120.5**		
90.9	97.7	104.5	6		6			6	126	-120	
92.7	97.7	102.7	6		6			6	126	-120	
93.5	97.7	101.9	6		6			6	126	-120	
99.3	101.9	104.5	6	5.6	11.6	20	15.5	16.1	120.3	-104.2	
100.9	102.7	104.5	6	5.8	11.8	20	5.8	26	119.6	-93.6	
101.1	101.9	102.7	6	5.9	11.9	40	11	40.9	120.3	-79.4	Local Carrier KONO 101.1
103.5	102.7	101.9	6	6	12	40	20	32	119.6	-87.6	
106.1	101.9	97.7	6	6	12	20	12	20	120.3	-100.3	
106.3	104.5	102.7	6	6	12	20	1	31	120.5	-89.5	
107.1	104.5	101.9	6	5.6	11.6	20	11.4	20.2	120.5	-100.3	
107.7	102.7	97.7	6	6.2	12.2	20	8.4	23.8	119.6	-95.8	
111.3	104.5	97.7	6	5.8	11.8	20	20	11.8	120.5	-108.7	
Local Stations in the Area											