

**Occupied Bandwidth and
Spurious Emissions Measurements**
To Demonstrate Compliance with
Section 73.317(b) through 73.317(d) of the
FCC Rules and Regulations

Clear Channel Broadcasting Licenses, Inc.
WXSJ(FM) – 101.5 MHz
Quincy, FL (Facility ID No: 25022)
WOKL(FM) – 100.7 MHz
Midway, FL (Facility ID No: 5379)
February 13, 2002

Measurements were conducted to demonstrate that WXSJ(FM), Quincy, FL and WOKL(FM), Midway, FL operating into a combined antenna system as specified in Construction Permit BPH-19961230IA, comply with section 73.317(b) through 73.317(d) of the FCC Rules and Regulations (a Construction Permit was not required for WOKL(FM) since the Effective Radiation Power and the Antenna Height Above Average Terrain remain unchanged). The measurements were conducted on February 13, 2002 by Randall L. Mullinax, with both stations simultaneously utilizing the shared antenna as specified in "Special operating conditions or restrictions 3." of the Construction Permit. The spectrum analyzer used for the measurements was a Tektronix model 2710, S/N B020735. A sample of the WXSJ(FM) and WOKL(FM) signals was derived from the main transmission line at the output of the combiner and was coupled to the analyzer using a short length of RG-142 50Ω double-shielded coaxial cable. Two 6 dB pads (Bird model 5-A-MFN-06) were inserted ahead of the analyzer to avoid overload and to provide isolation.

The unmodulated carrier level of WXSJ(FM) was +18 dBm and the unmodulated carrier level of WOKL(FM) was +13 dBm. Since the WOKL(FM) reference level was lower, it was used as the reference for all harmonic, spurious and intermodulation measurements. All measurements were conducted with the transmitters and associated equipment adjusted as used in normal program operation.

For all occupied bandwidth measurements, the spectrum analyzer was placed in the peak hold mode for at least 10 minutes per measurement before the waveforms were observed. Both transmitters were observed to be in full compliance with section 73.317(b) of the FCC Rules with emissions appearing on frequencies removed from the carrier frequencies by between 120 kHz and 240 kHz attenuated by at least 25 dB below the unmodulated carrier level indicating the occupied bandwidth of each transmitter to be 240 kHz or less. Both transmitters were also observed to be in full compliance with section 73.317(c) of the FCC Rules with emissions appearing on frequencies removed from the carrier frequencies by between 240 kHz and 600 kHz attenuated by at least 35 dB.

Extensive measurement were also conducted to insure that emissions appearing on frequencies removed from the carrier frequencies by more than 600 kHz were attenuated by at least 80 dB as required by section 73.317(d) of the FCC Rules. To facilitate these measurements, notch filters were placed between the two 6 dB pads so that the spectrum analyzer gain could be increased by 10 dB. The filters were necessary to avoid the possible generation of false spurious or intermodulation products in the analyzer. The attenuation of the notch filters was 39.8 dB at 101.5 MHz and 40.1 dB at 100.7 MHz.

All harmonic and intermodulation frequencies in the range of frequencies between 5 MHz and 1000 MHz through the 3rd order that could be produced by the combined

operation of WXSJ(FM) and WOKL(FM) were predicted with a computer program, the results of which are shown in Table 1.

TABLE 1

Frequency No. 1:		100.7											
Frequency No. 2:		101.5											
Maximum Order Of Products Checked: 3													
#	Order	x	Freq.	Sum/Dif	Order	x	Freq.	=	Product				
1.	1	x	100.7	+	1	x	101.5	=	202.2				
2.	1	x	101.5	+	1	x	100.7	=	202.2				
3.	1	x	100.7	+	2	x	101.5	=	303.7				
4.	1	x	101.5	+	2	x	100.7	=	302.9				
5.	1	x	100.7	+	3	x	101.5	=	405.2				
6.	1	x	101.5	+	3	x	100.7	=	403.6				
7.	2	x	100.7	=				=	201.4				
8.	2	x	100.7	+	1	x	101.5	=	302.9				
9.	2	x	100.7	-	1	x	101.5	=	99.9				
10.	2	x	101.5	=				=	203				
11.	2	x	101.5	+	1	x	100.7	=	303.7				
12.	2	x	101.5	-	1	x	100.7	=	102.3				
13.	2	x	100.7	+	2	x	101.5	=	404.4				
14.	2	x	101.5	+	2	x	100.7	=	404.4				
15.	2	x	100.7	+	3	x	101.5	=	505.9				
16.	2	x	101.5	+	3	x	100.7	=	505.1				
17.	3	x	100.7	=				=	302.1				
18.	3	x	100.7	+	1	x	101.5	=	403.6				
19.	3	x	100.7	-	1	x	101.5	=	200.6				
20.	3	x	101.5	=				=	304.5				
21.	3	x	101.5	+	1	x	100.7	=	405.2				
22.	3	x	101.5	-	1	x	100.7	=	203.8				
23.	3	x	100.7	+	2	x	101.5	=	505.1				
24.	3	x	100.7	-	2	x	101.5	=	99.1				
25.	3	x	101.5	+	2	x	100.7	=	505.9				
26.	3	x	101.5	-	2	x	100.7	=	103.1				
27.	3	x	100.7	+	3	x	101.5	=	606.6				
28.	3	x	101.5	+	3	x	100.7	=	606.6				
#	Order	x	Freq.	Plus	Order	x	Freq.	Minus	Order	x	Freq.	=	Product
No More Frequency Products Within Desired Range													


While special attention was given to the “product” frequencies listed in Table 1, measurements were conducted covering the entire range of frequencies between 5 MHz and 1000 MHz. The only signals detected at levels attenuated by less than 80 dB below the unmodulated carrier levels and appearing on frequencies removed from the WXSJ(FM) and WOKL(FM) carrier frequencies by more than 600 kHz were the carriers of nearby FM and Television stations. In each case where these signals were observed to be at a level greater than -67 dBm (80 dB below the unmodulated carrier level of WOKL(FM) which was +13 dBm) both the WXSJ(FM) and WOKL(FM) transmitters were turned off while the amplitude of the signal was observed to be unchanged, indicating that the signal was not the result of the combined operation of WXSJ(FM) and WOKL(FM).

Results of the measurements at the specific frequencies where harmonic or intermodulation products were predicted to possibly occur are shown in Table 2.

TABLE 2

DESCRIPTION	FREQ. MHz	ATTENUATION dB	DESCRIPTION	FREQ. MHz	ATTENUATION dB
100.7 + 101.5	202.2	90	(3 X 101.5) - 100.7	203.8	90
(2 X 101.5) + 100.7	303.7	90	(3 X 100.7) - (2 X 101.5)	99.1	90
(2 X 100.7) + 101.5	302.9	90	(3 X 101.5) - (2 X 100.7)	103.1	90
(3 X 101.5) + 100.7	405.2	90	(3 X 100.7) + (3 X 101.5)	606.6	90
(3 X 100.7) + 101.5	403.6	90	4 X 100.7	402.8	90
2 X 100.7	201.4	90	4 X 101.5	406.0	90
(2 X 100.7) - 101.5	99.9	86	5 X 100.7	503.5	90
2 X 101.5	203.0	90	5 X 101.5	507.5	90
(2 X 101.5) - 100.7	102.3	82	6 X 100.7	604.2	90
(2 X 100.7) + (2 X 101.5)	404.4	90	6 X 101.5	609.0	90
(2 X 100.7) + (3 X 101.5)	505.9	90	7 X 100.7	704.9	90
(2 X 101.5) + (3 X 100.7)	505.1	90	7 X 101.5	710.5	90
3 X 100.7	302.1	90	8 X 100.7	805.6	90
(3 X 100.7) - 101.5	200.6	90	8 X 101.5	812.0	90
3 X 101.5	304.5	90	9 X 100.7	906.3	90
			9 X 101.5	913.5	82

The results of these measurements confirm that the combined operations of WXSJ(FM) and WOKL(FM) into a shared antenna are in full compliance with section 73.317(b) through 73.317(d) of the FCC Rules and Regulations.



Randall L. Mullinax
Regional Engineering Services Manager
Clear Channel Broadcasting Licenses, Inc.