



1425 East Jackson Street Suite O
Thomasville, GA 31792
702-825-0287
[**reelaudio@gmail.com**](mailto:reelaudio@gmail.com)

W257BS TPO Calculation

Transmitter power output: **43 watts TPO**

Antenna Power Gain Multiplier = 1.396

Antenna efficiency = **139.6%**

Feedline = 215 feet of Andrew LDF5-50 7/8" foam line,

LDF5-50 Line Loss at 99.3 mhz = .3617 db/100ft

Total coax loss = 0.778db

Line efficiency = **83.6%**

$43 \text{ watts} \times 1.396 \times 0.836 = 50$

50 watts ERP

-Chris Hall

Owner/Operator Reel Audio Broadcast Engineering, Inc.

A handwritten signature in black ink, appearing to be 'Chris Hall', written in a cursive style.