



2xCA2-FM/CP/CV array

1 antenna skewed 174 deg. / 25% power

1 antenna skewed 307 deg. / 75% power

Max Gain: -0.2 dBd

power-x: .95

Circular Polarization

Horizontal Plane Pattern



2xCA2-FM/CP/CV array

1 antenna skewed 174 deg. / 25% power

1 antenna skewed 307 deg. / 75% power

Max Gain: -0.2 dBd

power-x: .95

Circular Polarization

Horizontal Plane Pattern

Angle	Field	Rel.dB	dBd	PwrMult	Angle	Field	Rel.dB	dBd	PwrMult
0	0.622	-4.12	-4.32	0.37	180	0.585	-4.66	-4.86	0.33
10	0.439	-7.15	-7.35	0.18	190	0.549	-5.21	-5.41	0.29
20	0.239	-12.42	-12.62	0.05	200	0.498	-6.05	-6.25	0.24
30	0.127	-17.94	-18.14	0.02	210	0.438	-7.18	-7.38	0.18
40	0.076	-22.44	-22.64	0.01	220	0.368	-8.68	-8.88	0.13
50	0.058	-24.69	-24.89	0.00	230	0.321	-9.87	-10.07	0.10
60	0.059	-24.61	-24.81	0.00	240	0.378	-8.45	-8.65	0.14
70	0.065	-23.79	-23.99	0.00	250	0.462	-6.70	-6.90	0.20
80	0.093	-20.65	-20.85	0.01	260	0.590	-4.58	-4.78	0.33
90	0.171	-15.32	-15.52	0.03	270	0.714	-2.92	-3.12	0.49
100	0.260	-11.71	-11.91	0.06	280	0.817	-1.76	-1.96	0.64
110	0.392	-8.13	-8.33	0.15	290	0.898	-0.94	-1.14	0.77
120	0.508	-5.88	-6.08	0.25	300	0.948	-0.47	-0.67	0.86
130	0.596	-4.49	-4.69	0.34	310	0.981	-0.17	-0.37	0.92
140	0.652	-3.72	-3.92	0.41	320	0.996	-0.04	-0.24	0.95
150	0.687	-3.27	-3.47	0.45	330	0.953	-0.42	-0.62	0.87
160	0.690	-3.22	-3.42	0.46	340	0.873	-1.18	-1.38	0.73
170	0.638	-3.90	-4.10	0.39	350	0.767	-2.31	-2.51	0.56