



Values in Relative Field

Site: WMEL-LD
Channel: 13

Model: JSL-4V / D13 SEC
Description: VHF Slot Antenna
Notes: Blue = H-Pol; Red = V-Pol



Azimuth Pattern Tabulation

<u>AZIMUTH</u>	<u>H-Pol</u>	<u>V-Pol</u>
0	0.920	0.920
10	0.930	0.920
20	0.940	0.905
30	0.960	0.890
40	0.980	0.860
50	0.990	0.820
60	1.000	0.780
70	0.980	0.720
80	0.950	0.650
90	0.900	0.580
100	0.840	0.500
110	0.760	0.410
120	0.670	0.330
130	0.570	0.280
140	0.470	0.240
150	0.380	0.210
160	0.320	0.200
170	0.270	0.200
180	0.280	0.200
190	0.270	0.200
200	0.320	0.200
210	0.380	0.210
220	0.470	0.240
230	0.570	0.280
240	0.670	0.330
250	0.760	0.410
260	0.840	0.500
270	0.900	0.580
280	0.950	0.650
290	0.980	0.710
300	1.000	0.780
310	0.980	0.820
320	0.960	0.860
330	0.940	0.890
340	0.930	0.905
350	0.920	0.920

Site: WMEL-LD
Channel: 13

Model: JSL-4V / D13 SEC
Description: VHF Slot Antenna
Notes: Blue = H-Pol; Red = V-Pol