

CP190345

Antenna: CA2-FM/CP array

02-03-2017

Frequency: 107.3 MHz

Polarization: Circular

Azi muth	Fi el d	Rel . dB	dBd	Pwr Gai n
0	0. 981	-0. 2	-0. 9	0. 813
10	0. 927	-0. 7	-1. 4	0. 724
20	0. 833	-1. 6	-2. 3	0. 589
30	0. 719	-2. 9	-3. 6	0. 437
40	0. 562	-5. 0	-5. 7	0. 269
50	0. 354	-9. 0	-9. 8	0. 105
60	0. 131	-17. 7	-18. 4	0. 014
70	0. 063	-24. 0	-24. 7	0. 003
80	0. 055	-25. 2	-25. 9	0. 003
90	0. 053	-25. 5	-26. 3	0. 002
100	0. 058	-24. 7	-25. 4	0. 003
110	0. 080	-21. 9	-22. 7	0. 005
120	0. 228	-12. 8	-13. 6	0. 044
130	0. 463	-6. 7	-7. 4	0. 182
140	0. 645	-3. 8	-4. 5	0. 355
150	0. 785	-2. 1	-2. 8	0. 525
160	0. 887	-1. 0	-1. 8	0. 661
170	0. 961	-0. 3	-1. 1	0. 776
180	1. 000	-0. 0	-0. 7	0. 851
190	0. 996	-0. 0	-0. 8	0. 832
200	0. 945	-0. 5	-1. 2	0. 759
210	0. 827	-1. 7	-2. 4	0. 575
220	0. 720	-2. 9	-3. 6	0. 437
230	0. 617	-4. 2	-4. 9	0. 324
240	0. 492	-6. 2	-6. 9	0. 204
250	0. 342	-9. 3	-10. 1	0. 098
260	0. 178	-15. 0	-15. 7	0. 027
270	0. 114	-18. 8	-19. 6	0. 011
280	0. 262	-11. 6	-12. 4	0. 058
290	0. 423	-7. 5	-8. 2	0. 151
300	0. 557	-5. 1	-5. 8	0. 263
310	0. 667	-3. 5	-4. 3	0. 372
320	0. 768	-2. 3	-3. 0	0. 501
330	0. 893	-1. 0	-1. 7	0. 676
340	0. 973	-0. 2	-1. 0	0. 794
350	0. 999	-0. 0	-0. 8	0. 832