



2xCA5-FM/CP/RM/CV array

1 antenna skewed 0 deg. w/97.3% power

1 antenna skewed 106 deg. w/2.7% power

Max Gain: 5.3 dB

power:3.39

Circular Polarization

Horizontal Plane Pattern



2xCA5-FM/CP/RM/CV array

1 antenna skewed 0 deg. w/97.3% power

1 antenna skewed 106 deg. w/2.7% power

Max Gain: 5.3 dB

power:3.39

Circular Polarization

Horizontal Plane Pattern

Angle	Field	Rel.dB	dBd	PwrMult	Angle	Field	Rel.dB	dBd	PwrMult
0	1.000	0.00	5.30	3.39	180	0.209	-13.59	-8.29	0.15
10	0.951	-0.43	4.87	3.07	190	0.200	-13.97	-8.67	0.14
20	0.864	-1.27	4.03	2.53	200	0.182	-14.79	-9.49	0.11
30	0.719	-2.87	2.43	1.75	210	0.161	-15.86	-10.56	0.09
40	0.535	-5.43	-0.13	0.97	220	0.149	-16.52	-11.22	0.08
50	0.357	-8.94	-3.64	0.43	230	0.161	-15.85	-10.55	0.09
60	0.250	-12.06	-6.76	0.21	240	0.186	-14.60	-9.30	0.12
70	0.228	-12.83	-7.53	0.18	250	0.201	-13.92	-8.62	0.14
80	0.263	-11.59	-6.29	0.24	260	0.199	-14.04	-8.74	0.13
90	0.299	-10.49	-5.19	0.30	270	0.180	-14.91	-9.61	0.11
100	0.333	-9.54	-4.24	0.38	280	0.168	-15.52	-10.22	0.10
110	0.340	-9.36	-4.06	0.39	290	0.161	-15.89	-10.59	0.09
120	0.315	-10.04	-4.74	0.34	300	0.212	-13.47	-8.17	0.15
130	0.267	-11.48	-6.18	0.24	310	0.343	-9.29	-3.99	0.40
140	0.224	-12.99	-7.69	0.17	320	0.533	-5.47	-0.17	0.96
150	0.203	-13.86	-8.56	0.14	330	0.716	-2.90	2.40	1.74
160	0.198	-14.08	-8.78	0.13	340	0.864	-1.27	4.03	2.53
170	0.201	-13.95	-8.65	0.14	350	0.953	-0.42	4.88	3.07